

orxCAMERA structure

Summary

```
[CameraTemplate]
FrustumHeight = <float>
FrustumWidth  = <float>
FrustumNear   = <float>
FrustumFar    = <float>
ParentCamera  = CameraTemplate
Position      = <vector>
Rotation      = <float>
Zoom          = <float>
GroupList     = Group1 # ... # GroupN
```

Details

Here's a list of the available properties for an orxCAMERA structure:

- FrustumNear/FrustumFar: Defines the near and far planes for the [camera frustum](#). The near plane is excluded whereas the far plane is included when doing render culling.
- FrustumHeight/FrustumWidth: As orx's cameras are 2D ones, their frustum are [rectangle cuboids](#) instead of real [frustums](#). If you want to achieve a 1:1 aspect ratio with your main display window, you can use the `Display.ScreenHeight` and `Display.ScreenWidth` values.
- ParentCamera: If defined, this camera will be a child of the other camera in the same way it's done for orxOBJECTs that have a ParentCamera property.
- Position: Camera's initial position.
- Rotation: Camera's initial rotation (along its Z-axis).
- Zoom: Camera's initial zoom.
- GroupList: Groups (of objects) will be rendered in the order of declaration. Up to 16 groups can be associated to a camera. Defaults to "default" group. ¹⁾

¹⁾

Good discussions on GroupList rendering orders can be found at <http://orx-project.org/forum?func=view&catid=16&id=7254#7279> and <http://orx-project.org/forum?func=view&catid=12&id=7344>

From:
<https://www.orx-project.org/wiki/> - **Orx Learning**

Permanent link:
https://www.orx-project.org/wiki/en/orx/config/settings_structure/orxcamera?rev=1419895804

Last update: **2025/09/30 17:26 (7 months ago)**

