

Combination Keys with CombineList

Config

```
[MainInput]
KEY_ENTER = Select # ToggleFullScreenMode ;E.g. Enter key is used for two
different actions
KEY_RALT = ToggleFullScreenMode ;Right-Alt and Enter keys are both set for
ToggleFullScreenMode

CombineList = ToggleFullScreenMode ;Must be combined to trigger the
ToggleFullScreenMode action
```

Code

```
if (orxInput_HasBeenActivated("ToggleFullScreenMode")){
    orxDisplay_SetFullScreen(!orxDisplay_IsFullScreen());
}
```

From:

<https://www.orx-project.org/wiki/> - **Orx Learning**

Permanent link:

https://www.orx-project.org/wiki/en/examples/input/combination_keys_with_combinelist

Last update: **2025/09/30 17:26 (3 months ago)**

